



Models	EG6500CX
DRIVE	
AC Frequency (hz)	50
AC Output Voltage (V)	220
Rated AC Output (kVA)	5
Max AC Output (kVa)	5,5
DC Output	12V-8.3A
Max Power Output (kW)	
Continuous Operating Hours (hrs)	8,1
Operating Noise Level @ 7m (dB(A))	99
ENGINE	
Model	GX390
Type	Air-cooled, 4 stroke, OHV, single cylinder
Displacement (cc)	389
Ignition System	Transistorized Magneto
Starting System	Recoil
Fuel Tank Capacity (l)	24
DIMENSIONS AND WEIGHT	
Dimensions (L x W x H) (mm)	681 x 530 x 571
Dry weight (kg)	84
FEATURES	
Eco Throttle	No
Oil Alert	Yes
Fuel Gauge	Yes
Large Capacity Fuel Tank	Yes
Capacity Air Cleaner	Yes
Large Capacity Muffler	Yes
Large Capacity Fuel Cleaner	No
Accessory AC Plug	Yes
Automatic Voltage Regulator	Yes
Voltmeter	Yes
AC Circuit Breaker	Yes
DC Circuit Breaker	Yes
Parallel Operation Connection Ports	N/A
Parallel Operation Connection Cable	
2/4-Wheel Dolly Kit	N/A
Electric Starter	No
Battery Tray Kit	No
Pilot Lamp	N/A
Receptacle 1	Standard 3 pin type D/ twist lock 16A
Receptacle 2	Standard 3 pin type D/ twist lock 16A
Receptacle 3	N/A

DISCLAIMER

Whilst Honda Motor Southern Africa takes reasonable care to ensure the accuracy and completeness of any data or information provided by it on this web site, any person accessing this web site agrees that by so accessing this web site that Honda Motor

Southern Africa, its officers, employees and agents do not accept any liability of whatsoever nature for any direct, indirect, incidental or consequential loss or damage of any kind or nature, howsoever arising from the use of or reliance on any such data or information Please note all prices featured on the Honda Motor Southern Africa web site are manufacturer recommended prices and indicative only.